

Tork Digital Timer

For Low Voltage Lighting Systems



This timer is designed to activate low voltage lighting transformers, lights, motor driven devices, fountains, etc.

It calculates the time for dusk and dawn for every day of the year. Devices can be turned on and off at specific times of the day or at sunrise/sunset. Automatically adjusts for daylight savings time.

Features

- 3-prong grounded male plug
- Dual-timed, grounded outlets go on and off simultaneously (one on the left and the other on the bottom of the timer)
- Easy-to-read liquid crystal display
- Flexible programming capabilities; up to 20 ON/OFF settings with manual ON/OFF button for immediate override
- Digital timing accuracy to one minute per year; time of day can be programmed to the second for synchronizing multiple transformers on a property
- Can be programmed while unplugged and taken to a job site

Technical Data

- 120 VAC, 60 Hertz
- 15 Amps* (1800 Watts) Resistive
- 960 Watts* tungsten
- 1/3 Horsepower

**Total for the combined load on both receptacles at 120VAC.*

