

HEAVY DUTY OUTDOOR DIGITAL TIMER

**Automatically
 control lawn,
 garden, holiday
 and security
 lights.**



FEATURES

1. Battery Holder (back of unit) - two LR44 batteries keep time up to three months without power.
2. Low Battery Indicator - programmed data is stored in non-volatile memory, so it won't be lost when batteries are removed.
3. Time Of Day (TOD) Display - the timer will automatically adjust for Daylight Saving Time (DST) and changing dawn and dusk times for your location (Astronomic feature)
4. Push buttons
5. Two Timed, Grounded Outlets
6. Selector Knob
7. Reset Button
8. Day Of Week (DOW) Display - events can be programmed for just one day of the week, all the days of the week, just weekdays or just weekends.
9. Event Display - the timer can be programmed for up to 28 total ON/OFF events per week.
10. Mode Display - the timer can display several modes during setup and programming and three modes during operation: **MANual**, **AUTO**, **RANDom**. **MANual** allows for manual operation of the plugged-in devices, **AUTO** uses the timer's exact settings and **RANDom** uses the timer's settings varied by random 5-minutes increments of +/- 30 minutes.
11. Output Status Indicator - this is the ON/OFF indicator. When the green light is on it means that the lamp or appliance should be on. If it is not on, the bulb may be burned out or the device may be turned off a the lamp or appliance.

